

Kurulum

<https://learn.microsoft.com/en-us/sysinternals/downloads/sysmon> adresinden sysmon indirilir.

Cmd ile indirilen dosya konumuna gidilir ardından Sysmon'u default ayarlarda çalıştırmak için "Sysmon.exe -i -accepteula" komutu girilir.

```
Directory of C:\Users\...\.Downloads\Sysmon
02.10.2023  10:21    <DIR>          .
02.10.2023  10:21    <DIR>          ..
27.06.2023  16:54                7.490 Eula.txt
27.06.2023  16:55           8.443.704 Sysmon.exe
27.06.2023  16:55           4.548.864 Sysmon64.exe
27.06.2023  16:55           4.989.200 Sysmon64a.exe
            4 File(s)      17.989.258 bytes
            2 Dir(s)    340.618.387.456 bytes free

C:\Users\...\.Downloads\Sysmon>Sysmon.exe -i -accepteula

System Monitor v15.0 - System activity monitor
By Mark Russinovich and Thomas Garnier
Copyright (C) 2014-2023 Microsoft Corporation
Using libxml2. libxml2 is Copyright (C) 1998-2012 Daniel Veillard. All Rights Reserved.
Sysinternals - www.sysinternals.com

Sysmon installed.
SysmonDrv installed.
Starting SysmonDrv.
SysmonDrv started.
Starting Sysmon..
Sysmon started.
```

Sysmon kullanımına ait detayları görmek için Sysmon -h komutu kullanılır.

```
\Downloads\Sysmon>sysmon -h
```

```
System Monitor v15.0 - System activity monitor  
By Mark Russinovich and Thomas Garnier  
Copyright (C) 2014-2023 Microsoft Corporation  
Using libxml2. libxml2 is Copyright (C) 1998-2012 Daniel Veillard. All Rights Reserved.  
Sysinternals - www.sysinternals.com
```

Usage:

```
Install:           Sysmon.exe -i [<configfile>]  
Update configuration: Sysmon.exe -c [<configfile>]  
Install event manifest: Sysmon.exe -m  
Print schema:      Sysmon.exe -s  
Uninstall:         Sysmon.exe -u [force]  
-c Update configuration of an installed Sysmon driver or dump the  
    current configuration if no other argument is provided. Optionally  
    take a configuration file.  
-i Install service and driver. Optionally take a configuration file.  
-m Install the event manifest (done on service install as well)).  
-s Print configuration schema definition of the specified version.  
    Specify 'all' to dump all schema versions (default is latest)).  
-u Uninstall service and driver. Adding force causes uninstall to proceed  
    even when some components are not installed.
```

The service logs events immediately and the driver installs as a boot-start driver to capture activity from early in the boot that the service will write to the event log when it starts.

On Vista and higher, events are stored in "Applications and Services Logs/Microsoft/Windows/Sysmon/Operational". On older systems, events are written to the System event log.

Use the '-? config' command for configuration file documentation. More examples are available on the Sysinternals website.

Specify -accepteula to automatically accept the EULA on installation, otherwise you will be interactively prompted to accept it.

Neither install nor uninstall requires a reboot.

Revision #1

Created 27 January 2024 15:57:34 by Ertan Sözer

Updated 27 January 2024 15:58:33 by Ertan Sözer